



C-Band Interference Elimination Filter

Model 13961W

Ideal for eliminating interference from WiMAX, RADAR and virtually any other potential source of out-of-band interference.

The model 13961W combines innovative design techniques with the solid performance of its renowned predecessor (model 13961).



Utilizing a durable and true one piece body/flange construction, the 13961W is shipped with hardware & gasketing and is ready to install between the feedhorn and the LNB/LNA.

No other manufacturer's C-band interference elimination filter offers all of these features:

Length:	5.49" (13.9 cm)
Weight:	1.125 lbs (0.51 kg)
Passband VSWR:	1.44:1 Typ; 1.5:1 Max
Group Delay Variation:	7 nS Max
Rejection :	45 dB Min @ 3.65 GHz / 4.25 GHz 60 dB Typ @ 3.55 GHz / 4.35 GHz 70 dB Typ @ 3.50 GHz / 4.40 GHz

Other Specifications:

Passband:	3.7 - 4.2 GHz
Passband Loss:	0.5 dB Approx. @ center band 0.5 dB Approx. roll off @ band edges
Transmit Band Rejection:	> 70 dB Typ from 5.8-6.725 GHz
Flanges:	CPR229G (Input) CPR229F (Output)
Finish:	Gloss White Lacquer

- (Standard Band) Passband Variations are typically available at no additional cost
- Typically in stock for same/next day shipping
- For international (Extended) Bands: See Pages 6 & 7

Marker

1	3.500000 GHz -80.580 dB
2	3.550000 GHz -59.765 dB
3	3.650000 GHz -45.593 dB
4	3.700000 GHz -0.7973 dB
5	3.950000 GHz -0.4502 dB
6	4.200000 GHz -0.8706 dB
7	4.250000 GHz -45.423 dB
8	4.350000 GHz -57.927 dB
9	4.400000 GHz -70.079 dB

